

**Listing of Claims:**

This listing of claims reflects all claim amendments and replaces all prior versions, and listings, of claims in the application. Material to be inserted is in underline, and material to be deleted is in ~~strikeout~~ or (if the deletion is of five or fewer consecutive characters or would be difficult to see) in double brackets [[ ]]. Any cancellations are without prejudice.

1-5. (Cancelled).

6. (Previously presented) A fast-locking phase-locked loop system configured to produce an output signal having a desired characteristic based on an applied reference signal, comprising:

a voltage controlled oscillator configured to produce the output signal;

a charge pump system operatively coupled with the voltage controlled oscillator and configured to generate currents that control the phase and frequency of the output signal produced by the voltage controlled oscillator, where the charge pump system includes:

at least one run-time charge pump configured to repeatedly pump charge during run-time operation of the phase-locked loop so as to produce ongoing phase adjustments of the output signal as needed to maintain the phase-locked loop in a locked condition; and

at least one additional charge pump configured to provide a charge pump current of substantially larger magnitude than that provided by the run-time charge pump so as to provide frequency adjustment of the output signal upon detection of cycle slippage between the output signal and the reference signal; and

an error detector operatively coupled with the charge pump system and configured to provide an error signal to the charge pump system upon which the charge pump currents are based, where the error detector includes a cycle slip detector configured to detect cycle slippage between the output signal and the reference signal, and where the cycle slip detector is configured to apply an activating signal to the additional charge pump upon detection of cycle slippage occurring between the output signal and the reference signal, the cycle slip detector including edge-triggered latches coupled with U and D outputs of a phase frequency detector.

7. (Original) The system of claim 6, where the latches are triggered by edges of input signals applied to the phase frequency detector.

8. (Previously presented) A fast-locking phase-locked loop system configured to produce an output signal having a desired characteristic based on an applied reference signal, comprising:

a voltage controlled oscillator configured to produce the output signal;

a charge pump system operatively coupled with the voltage controlled oscillator and configured to generate currents that control the phase and frequency of the output signal produced by the voltage controlled oscillator, where the charge pump system includes:

at least one run-time charge pump configured to repeatedly pump charge during run-time operation of the phase-locked loop so as to produce ongoing phase adjustments of the output signal as needed to maintain the phase-locked loop in a locked condition; and

at least one additional charge pump configured to provide a charge pump current of substantially larger magnitude than that provided by the run-time charge pump so as to provide frequency adjustment of the output signal upon detection of cycle slippage between the output signal and the reference signal; and

a bias generator operatively coupled with the voltage controlled oscillator and configured to generate a biasing current and an associated biasing signal based on differences between the output signal and the desired characteristic, where the phase-locked loop system is configured so that:

the biasing current produces a regulated bias generator voltage within the bias generator;

the voltage controlled oscillator produces the output signal in response to a VCO current generated via application of the biasing signal from the bias generator;

the VCO current produces a regulated VCO voltage within the voltage controlled oscillator; and

the regulated bias generator voltage matches the regulated VCO voltage free of any direct coupling between the bias generator and the regulated VCO voltage.

9. (Original) The system of claim 8, where the bias generator is configured to dynamically generate the biasing signal free of any predetermined external bias.

10. (Original) The system of claim 8, where the voltage controlled oscillator includes a plurality of VCO stages.

11. (Original) The system of claim 10, where the VCO stages are coupled in parallel between a positive voltage supply and a regulated ground node.

12. (Original) The system of claim 11, where the VCO current is produced by a VCO current source that is biased by the biasing signal, and where the VCO current source is coupled in series between a negative voltage supply and the regulated ground node.

13. (Original) The system of claim 11, where the VCO stages are coupled in parallel between a negative voltage supply and a regulated supply node.

14. (Original) The system of claim 13, where the VCO current is produced by a VCO current source that is biased by the biasing signal, and where the VCO current source is coupled in series between a positive voltage supply and the regulated supply node.

15. (Previously presented) A fast-locking phase-locked loop system configured to produce an output signal having a desired characteristic based on an applied reference signal, comprising:

a voltage controlled oscillator configured to produce the output signal;

a charge pump system operatively coupled with the voltage controlled oscillator and configured to generate currents that control the phase and frequency of the output signal produced by the voltage controlled oscillator, where the charge pump system includes:

at least one run-time charge pump configured to repeatedly pump charge during run-time operation of the phase-locked loop so as to produce ongoing phase adjustments

of the output signal as needed to maintain the phase-locked loop in a locked condition;  
and

at least one additional charge pump configured to provide a charge pump current of substantially larger magnitude than that provided by the run-time charge pump so as to provide frequency adjustment of the output signal upon detection of cycle slippage between the output signal and the reference signal;

where the charge pump system and voltage controlled oscillator are configured to be driven at least partially in response to application of a shared biasing signal which is generated based on detected differences between the output signal and the desired characteristic, and where the biasing signal is coupled into the charge pump system via an isolated input path configured to inhibit undesired signal coupling from the charge pump system to the voltage controlled oscillator via the shared biasing signal.

16. (Original) The system of claim 15, where the isolated input path includes a current mirror configured to produce a mirrored copy of the biasing signal for use within the charge pump system.

17. (Original) The system of claim 15, further comprising a bias generator configured to dynamically generate the biasing signal free of any predetermined external bias.

18. (Original) The system of claim 15, where the voltage controlled oscillator includes a current source and a plurality of VCO stages connected to the current source via a regulated voltage node, the voltage controlled oscillator being configured to produce the output signal based upon current supplied via the regulated voltage node to the plurality of VCO stages.

19. (Original) The system of claim 15, where the biasing signal is generated by a bias generator that matches an effective impedance of the voltage controlled oscillator so that current supplied to the voltage controlled oscillator is substantially independent of supply and substrate noise.

20. (Previously presented) A fast-locking phase-locked loop system configured to produce an output signal having a desired characteristic based on an applied reference signal, comprising:

a voltage controlled oscillator configured to produce the output signal;

a charge pump system operatively coupled with the voltage controlled oscillator and configured to generate currents that control the phase and frequency of the output signal produced by the voltage controlled oscillator, where the charge pump system includes:

at least one run-time charge pump configured to repeatedly pump charge during run-time operation of the phase-locked loop so as to produce ongoing phase adjustments of the output signal as needed to maintain the phase-locked loop in a locked condition; and

at least one additional charge pump configured to provide a charge pump current of substantially larger magnitude than that provided by the run-time charge pump so as to provide frequency adjustment of the output signal upon detection of cycle slippage between the output signal and the reference signal; and

a bias generator configured to generate a biasing signal via operation of a feedback loop responsive to currents generated by the charge pump system, where the voltage controlled oscillator is configured to produce the output signal in response to application of the biasing signal,

where charge pump output is applied to the bias generator along a proportional control path and an integrating control path, the proportional control path including a current mirror isolation mechanism to prevent capacitance on the proportional control path from affecting dynamic response of the bias generator feedback loop.

21-33 (Cancelled).

34. (Previously presented) A phase-locked loop system, comprising:

a voltage controlled oscillator coupled with an error detector in a feedback configuration so as to produce an output signal having a desired characteristic that is based on a reference signal;

a charge pump system coupled with the voltage controlled oscillator and configured to produce currents to control phase and frequency of the output signal, where the charge pump system includes at least two charge pumps, one such charge pump being configured to deliver a higher charge pump current than the other to produce more rapid changes in the output signal than the other charge pump, and where the phase-locked loop system is configured to intermittently activate the higher-current charge pump upon satisfaction of a predetermined condition, where such predetermined condition is selected so as to be determinable during operation of the phase-locked loop; and

a bias generator operatively coupled with the voltage controlled oscillator and configured to generate a biasing current and an associated biasing signal based on differences between the output signal and the desired characteristic, where the phase-locked loop system is configured so that:

the biasing current produces a regulated bias generator voltage within the bias generator;

the voltage controlled oscillator produces the output signal in response to a VCO current generated via application of the biasing signal from the bias generator;

the VCO current produces a regulated VCO voltage within the voltage controlled oscillator; and

the regulated bias generator voltage matches the regulated VCO voltage free of any direct coupling between the bias generator and the regulated VCO voltage.

35. (Original) The system of claim 34, where the bias generator is configured to dynamically generate the biasing signal free of any predetermined external bias.

36. (Original) The system of claim 34, where the voltage controlled oscillator includes a plurality of VCO stages.

37. (Original) The system of claim 36, where the VCO stages are coupled in parallel between a positive voltage supply and a regulated ground node.

38. (Original) The system of claim 37, where the VCO current is produced by a VCO current source that is biased by the biasing signal, and where the VCO current source is coupled in series between a negative voltage supply and the regulated ground node.

39. (Original) The system of claim 37, where the VCO stages are coupled in parallel between a negative voltage supply and a regulated supply node.

40. (Original) The system of claim 39, where the VCO current is produced by a VCO current source that is biased by the biasing signal, and where the VCO current source is coupled in series between a positive voltage supply and the regulated supply node.

41. (Previously presented) A phase-locked loop system, comprising:

a voltage controlled oscillator coupled with an error detector in a feedback configuration so as to produce an output signal having a desired characteristic that is based on a reference signal; and

a charge pump system coupled with the voltage controlled oscillator and configured to produce currents to control phase and frequency of the output signal,

where the charge pump system includes at least two charge pumps, one such charge pump being configured to deliver a higher charge pump current than the other to produce more rapid changes in the output signal than the other charge pump, and where the charge pump system and voltage controlled oscillator are configured to be driven at least partially in response to application of a shared biasing signal which is generated based on detected differences between the output signal and the desired characteristic, and where the biasing signal is coupled into the charge pump system via an isolated input path configured to inhibit undesired signal coupling from the charge pump system to the voltage controlled oscillator via the shared biasing signal.

42. (Original) The system of claim 41, where the isolated input path includes a current mirror configured to produce a mirrored copy of the biasing signal for use within the charge pump system.

43. (Original) The system of claim 41, further comprising a bias generator configured to dynamically generate the biasing signal free of any predetermined external bias.

44. (Original) The system of claim 41, where the biasing signal is generated by a bias generator that matches an effective impedance of the voltage controlled oscillator so that current supplied to the voltage controlled oscillator is substantially independent of supply and substrate noise.

45. (Previously presented) A phase-locked loop system, comprising:  
a voltage controlled oscillator coupled with an error detector in a feedback configuration so as to produce an output signal having a desired characteristic that is based on a reference signal;

a charge pump system coupled with the voltage controlled oscillator and configured to produce currents to control phase and frequency of the output signal, where the charge pump system includes at least two charge pumps, one such charge pump being configured to deliver a higher charge pump current than the other to produce more rapid changes in the output signal than the other charge pump; and

a bias generator configured to generate a biasing signal via operation of a feedback loop responsive to currents generated by the charge pump system, where the voltage controlled oscillator is configured to produce the output signal in response to application of the biasing signal,

and where charge pump output is applied to the bias generator along a proportional control path and an integrating control path, the proportional control path including a current mirror isolation mechanism to prevent capacitance on the proportional control path from affecting dynamic response of the bias generator feedback loop.

46 - 55. (Cancelled).



56. (Previously presented) The fast-locking phase-locked loop system of claim 6, where charge pump current is derived from a bias current inside the voltage controlled oscillator.

57. (Previously presented) The fast-locking phase-locked loop system of claim 8, where charge pump current is derived from a bias current inside the voltage controlled oscillator.

58. (Previously presented) The fast-locking phase-locked loop system of claim 15, where charge pump current is derived from a bias current inside the voltage controlled oscillator.

59. (Previously presented) The fast-locking phase-locked loop system of claim 20, where charge pump current is derived from a bias current inside the voltage controlled oscillator.

60. (Previously presented) The phase-locked loop system of claim 34, where charge pump current is derived from a bias current inside the voltage controlled oscillator.

61. (Previously presented) The phase-locked loop system of claim 41, where charge pump current is derived from a bias current inside the voltage controlled oscillator.